How to adjust power output

If your find the Power is too low when you transmitng on [Low power

output mode], the following steps can solve that problem.

Step1 Install TD-H8_TXPOWER_TUNE_setup221103



TD-H8_TXP OWER_TUN E_setup221 103

Step2 Open TD-H8_TXPOWER_TUNE



<u>Step3</u> Connect your radio with a programming cable, choice

corresponding port.

le Mac	TXPOWER_1 hine Edit	Program	Set Abou	t	*****		
NEW	open	SAVE	AS READ	© COM	MRITE	i) About	
	unication Pe munication						X
			ок	1	Cancel		

Step4 Click [WRITE]

The value of [Low Power] and [High Power] are default values that we recommend

If you find that the output power is still too low after adjustment, you can find the correct value by **adding or reducing 1** each time.

NEW	OPEN	Program SAVE	*	COM WRITE	() About	
	BAND	Low Power	Mid Power	High Power		
	136-140	61	115	255		
	140-150	58	110	255		
	150-160	52	105	255		
	160-170	50	105	255		
	170-	47	105	255		
	400-410	27	103	255		
	410-420	27	103	255		
	420-430	27	103	255		
	430-440	27	103	255		
	440-450	27	103	255		
	450-460	27	103	255		
	460-470	27	103	255		
	470-	27	103	255		
	245	55	118	255		

Please feel free to contact us if you encounter other problem Customer Support: support@tidradio.com